

60X60X38 mm

JF0638-11 Series



- **Frame** : Plastic Material UL 94V-0
- **Impeller** : Plastic Material UL 94V-0
- **Speed Range** : $\pm 10\%$

SPECIFICATIONS

Model	Bearing	Rated Voltage (V)	Operating Voltage (V)	Air Flow (CFM)	Static Pressure (inchH ₂ O)	Speed (R.P.M.)	Input Current (Amp)	Input Power (Watt)	Nominal Current (Amp)	Noise (dBA)	Weight (g)
JF0638B1TR	B	12	10.2 ~ 13.8	71.27	1.924	12000	1.46	17.52	1.61	64.3	113
JF0638B1UR				59.14	1.497	10500	0.92	11.04	1.01	59.5	
JF0638B1SR				53.92	1.049	9000	0.59	7.08	0.65	53.8	
JF0638B1HR				44.54	0.800	7500	0.40	4.80	0.44	49.2	
JF0638B1MR				35.53	0.452	6000	0.23	2.76	0.25	44.4	
JF0638B1LR				28.89	0.310	5000	0.18	2.16	0.20	37.4	
JF0638B1ER				25.35	0.241	4500	0.13	1.56	0.14	35.4	
JF0638B1VR				23.10	0.203	4000	0.10	1.20	0.11	33.2	
JF0638B2TR	B	24	20.4 ~ 27.6	71.27	1.924	12000	0.77	18.48	0.85	64.3	
JF0638B2UR				59.14	1.497	10500	0.48	11.52	0.53	59.5	
JF0638B2SR				53.92	1.049	9000	0.35	8.40	0.39	53.8	
JF0638B2HR				44.54	0.800	7500	0.19	4.56	0.21	49.2	
JF0638B2MR				35.53	0.452	6000	0.14	3.36	0.15	44.4	
JF0638B2LR				28.89	0.310	5000	0.12	2.88	0.13	37.4	
JF0638B2ER				25.35	0.241	4500	0.08	1.92	0.09	35.4	
JF0638B2VR				23.10	0.203	4000	0.07	1.68	0.08	33.2	

Specifications subject to change without notice

All models could be customized or are not listed above, please contact us.

B= Dual Ball bearing / N= NOVA -SLEEVE bearing / H= HTLS bearing / S= Sleeve bearing

